



# Cast Iron Condenser Motor



Beacon 35 and 50 watt condenser fan motors replace GEI and 21 frame series motors as well as EMS manufactured motors designed for commercial refrigeration units, large air conditioning units, and high volume air applications.

- 3 7/8" diameter
- UL recognized, CSA certified

UR Catalog Number	IRP Product Code Number	RPM	Watts Output	ROT	Volts	AMP	Shaft	Weight (lbs)	Equal To
35CW115	170-0001	1500	35	CW	115	1.4	1/4 X 20 THD	4.74	EMS # ESPL35M1
35CW230	170-0002	1500	35	CW	208-230	0.7	1/4 X 20 THD	4.74	EMS # ESPL35EM2
50CW115	170-0003	1500	50	CW	115	1.7	3/8 X 1 1/2	6.86	EMS # ESPL50EM1
50CW230	170-0004	1500	50	CW	208-230	0.85	3/8 X 1 1/2	6.96	EMS #ESPL50EM2
35CCW115	170-0005	1500	35	CCW	115	1.4	1/4 X 20 THD		EMS # ESPL35MR1
35CCW230	170-0006	1500	35	CCW	208-230	0.7	1/4 X 20 THD		EMS # ESPL35EMR2
50CCW15	170-0007	1500	50	CCW	115	1.7	3/8 X 1 1/2		EMS # ESPL50EMR1
50CCW230	170-0008	1500	50	CCW	208-230	0.85	3/8 X 1 1/2		EMS #ESPL50EMR2



# 35CW115

51 Frame, 3 1/2" Diameter, Shaded Pole, Single Shaft, Cast Iron, single speed, single rotation viewed opposite shaft end, 25" leads, permanent lubrication, side pad mounting, overload or impedance protection, 60/50 HZ, 1/4" Threaded Shaft - 1/2" Long, UL recognized and CSA certified



UR Catalog Number	IRP Product Code Number	RPM	Watts Output	ROT	Volts	AMP	Motor Width	Shaft	Weight (lbs)	Equal To
2.5CW115	170-0009	1550	2.5	CW	115	0.3	2 1/2"	1/4" THD x 1/2" LG	2.5	GE - 5KSP51AL611, Granger - 3M472, CPC - MTG5111, MARS - D5111, STEVCO - S5111
4CW115	170-0010	1550	4	CW	115	0.4	2 1/2"	1/4" THD x 1/2" LG	2.52	GE - 5KSP51AL511, Granger - 3M275, Emerson - RF115, CPC - MTG5211, MARS - D5211, STEVCO - S5211
4CCW115	170-0011	1550	4	CCW	115	0.4	2 1/2"	1/4" THD x 1/2" LG		GE - 5KSP51AL513, Granger - 3M274, Emerson - RF103, CPC - MTG5212, MARS - D5212, STEVCO - S5212
4CW230	170-0012	1550	4	CW	208-230	0.2	2 1/2"	1/4" THD x 1/2" LG	2.56	GE - 5KSP51AL512, CPC - MTG5221, MARS - D5221, STEVCO - S5221
4CCW230	170-0013	1550	4	CCW	208-230	0.2	2 1/2"	1/4" THD x 1/2" LG	2.56	GE - 5KSP51AL514, CPC - MTG5222, MARS - D5222, STEVCO - S5222
6CW115	170-0014	1550	6	CW	115	0.5	2 1/2"	1/4" THD x 1/2" LG	3.1	GE - 5KSP51CL501, Granger - 3M630, Emerson - RF117, CPC - MTG5311, MARS - D5311, STEVCO - S5311
6CCW115	170-0015	1550	6	CCW	115	0.5	2 1/2"	1/4" THD x 1/2" LG	3.14	GE - 5KSP51CL502, Granger - 3M269, Emerson - RF116, CPC - MTG5312, MARS - D5312, STEVCO - S5312
9CW115	170-0016	1550	9	CW	115	0.8	3"	1/4" THD x 1/2" LG	3.22	GE - 5KSP51ECL551, Granger - 3M285, Emerson - RF108, CPC - MTG5411, MARS - D5411, STEVCO - S5411
9CCW115	170-0017	1550	9	CCW	115	0.8	3"	1/4" THD x 1/2" LG	3.22	GE - 5KSP51ECL553, Granger - 3M284, Emerson - RF118, CPC - MTG5412, MARS - D5412, STEVCO - S5412
9CW230	170-0018	1550	9	CW	208-230	0.4	3"	1/4" THD x 1/2" LG	3.24	GE - 5KSP51ECL552, Granger - 3M286, Emerson - RF110, CPC - MTG5421, MARS - D5421, STEVCO - S5421
9CCW230	170-0019	1550	9	CCW	208-230	0.4	3"	1/4" THD x 1/2" LG	3.12	GE - 5KSP51ECL554, Granger - 3M283, Emerson - RF109, CPC - MTG5422, MARS - D5422, STEVCO - S5422
16CW115	170-0020	1550	16	CW	115	1.1	3 1/4"	1/4" THD x 1/2" LG	3.92	GE - 5KSP51GL581, Granger - 3M473, Emerson - RF112, CPC - MTG5811, MARS - D5811, STEVCO - S5811
16CCW115	170-0021	1550	16	CCW	115	1.1	3 1/4"	1/4" THD x 1/2" LG	3.82	GE - 5KSP51GL583, Granger - 3M475, Emerson - RF111, CPC - MTG5812, MARS - D5812, STEVCO - S5812
16CW230	170-0022	1550	16	CW	208-230	0.6	3 1/4"	1/4" THD x 1/2" LG	3.98	GE - 5KSP51GL582, Granger - 3M474, Emerson - RF114, CPC - MTG5821, MARS - D5821, STEVCO - S5821
16CCW230	170-0023	1550	16	CCW	208-230	0.6	3 1/4"	1/4" THD x 1/2" LG	3.86	GE - 5KSP51GL584, Granger - 3M476, Emerson - RF113, CPC - MTG5822, MARS - D5822, STEVCO - S5822